

TECHNICAL DATA

# Fluke PM8918/301 ScopeMeter Low Pass Filter Probe



## Product overview: Fluke PM8918/301 ScopeMeter Low Pass Filter Probe

One (blue) 10:1 probe for low frequency applications. Useful bandwidth is 4 kHz, reducing noise pick-up in noisy environments such as in automotive applications. The design is optimized for user's safety, double insulated according to IEC 1010-2-031 CAT III.

## Specifications: Fluke PM8918/301 ScopeMeter Low Pass Filter Probe

Specifications	
Probe length	2.5m (8 ft.)
Maximum signal voltage	600V rms. CAT III per IEC 1010-2-031
Maximum voltage to ground	600V rms. CAT III per IEC 1010-2-031
Attenuation	10x
Bandwidth	4 kHz
Input resistance	10 MΩ
Input capacitance	12.5pF



Compensation range	15 to 35 pF
When using the mini Test-hooks any potential must not exceed 42 Vpk / 30 Vrms	

## Ordering information



### **Fluke PM8918 301**

One (blue) 10:1 probe for low frequency applications. Useful bandwidth is 4 kHz, reducing noise pick-up in noisy environments such as in automotive applications. The design is optimized for user's safety, double insulated according to IEC 1010-2-031 CAT III.

---

Fluke. *Keeping your world up and running.*®

**Fluke Europe B.V.**

P.O. Box 1186  
5602 BD Eindhoven  
The Netherlands  
[www.fluke.com/en](http://www.fluke.com/en)

©2024 Fluke Corporation. All rights reserved.  
Data subject to alteration without notice.  
04/2024

**For more information call:**

In Middle East/Africa  
+31 (0)40 267 5100

**Modification of this document is not permitted  
without written permission from Fluke Corporation.**