

FLUKE®

**Fluke 317/319
True RMS Clamp Meters**

Accurate. Rugged. Safe.

New



Fluke 317/319

True RMS Clamp Meters

FLUKE®



Fluke 317, 319 functions: new/improved features

- Thin jaws and small, light body mean the meters are more suitable for use in confined spaces.
- Large 1000 A AC/DC current measurement with AC/DC voltage measurement.
- Inrush measurement technology allows measurement of starting current for devices such as motors and lightning equipment; integration time is 100 ms (Fluke 319 only).
- Frequency measurements enable accurate measurement of PWM output signal frequency (Fluke 319 only).
- True RMS AC/DC measurement
- Min/max function suitable for current and voltage
- Large easy to read, 6000 count backlit display
- 4000 Ω resistance measuring span
- Data hold function can save measurement results on the screen
- Continuity beeper $\leq 30 \Omega$
- Auto Power Off function maximises battery life span
- Clamp opening: 37 mm (1.45 inch)
- Warranty - 1 year

General specifications	
Power supply	3x AAA IEC LR03 batteries
Max. jaw opening	37 mm (1.45 in)
Jaw diameter	37 mm (1.45 in)
Dimensions (L x W x H)	234 mm x 74 mm x 34.8 mm
Weight	384 g (13.5 oz) (with battery)
Calibration	Fully manual calibration and testing, one year calibration testing period
Digital display resolution	6000 digits
Safety	CE EN/IEC 61010-1 and IEC 61010-2-032 Measurement category: 600 V CAT III (Category III)

Environmental indicators	
Working temperature	-10°C to 50°C (14°F to 122°F)
Storage temperature	-40°C to 60°C (-40°F to 140°F)
IP equivalent	IP40
Drop test requirements	Drop height tested to 1 m (3 ft), all six sides tested, oak flooring



Fluke 317/319

True RMS Clamp Meters

FLUKE®

Technical specifications			
Function	Parameter	Fluke 317	Fluke 319
AC Current	Measurement	40.00 A	40.00 A
		600.0 A	600.0 A
			1000 A
	Resolution	0.01 A	0.01 A
		0.1 A	0.1 A
			1 A
	Precision	Accuracy 1.6% ± 6 digits (50-60 Hz) [40 A]	1.6% ± 6 digits (50-60 Hz) [40 A]
		2.5% ± 8 digits (60-500 Hz) [40 A]	2.5% ± 8 digits (60-500 Hz) [40 A]
1.5% ± 5 digits (50-60 Hz) [600 A]		1.5% ± 5 digits (50-60 Hz) [600/1000 A]	
2.5% ± 5 digits (60-500 Hz) [600 A]		2.5% ± 5 digits (60-500 Hz) [600/1000 A]	
When crest factor CF > 2, increase the specifications by 2%	For 500 A, maximum 3.0	For 500 A, maximum 3.0	
	For 600 A, maximum 2.5	For 600 A, maximum 2.5	
AC response	RMS	RMS	
DC Current	Range	40.00 A	40.00 A
		600.0 A	600.0 A
			1000 A
	Resolution	0.01 A	0.01 A
		0.1 A	0.1 A
			1 A
Accuracy	1.6% ± 6 digits [40 A]	1.6% ± 6 digits [40 A]	
	1.5% ± 5 digits [600 A]		
AC voltage	Range	600.0 V	
	Resolution	0.1V	
	Accuracy	1.5% ± 5 digits (20-500Hz)	
	AC response	RMS	
DC voltage	Range	600.0 V	
	Resolution	0.1 V	
	Accuracy	1% ± 4 digits	
Resistance	Measurement	4000 Ω	
	Resolution	0.1 Ω	
		1.0 Ω	
	Accuracy	1% ± 5 digits	
Continuity		≤ 30 Ω	
Inrush current	Integration time	NA	100 ms
Frequency	Measuring span	NA	5.0-500.0 Hz
	Accuracy	NA	0.5% ± 5 digits
	Power level	NA	10 - 100 Hz ≥ 5 A, 5 - 10 Hz, 100 - 500 Hz ≥ 10 A



Fluke 317/319 True RMS Clamp Meters

- Frequency measurement (Fluke 319)
- Unique 40 A low frequency measurements capability with 0.01 A resolution, 1.6 % accuracy

Fluke 317/319 True RMS Clamp Meters

FLUKE®

Also available

DIGITAL MULTI METERS

FLUKE 15B / 17B



FLUKE 115



FLUKE 179 with TPAK



CLAMP METERS

FLUKE 322



FLUKE 374



FLUKE iFlex™



ADDITIONAL RANGE

FLUKE TL 175



LVD 2



FLUKE 62



Look out for this sticker on every Fluke test tool Packaging



Look out for this hologram sticker on every Fluke test tool



Look for Genuine Warranty Sticker

Fluke. Keeping your world up and running.®

FLUKE®

10th Floor, Sigma, Hiranandani Business Park,
Powai, Mumbai - 400076.INDIA.
Tel : 1 800 209 9110 (Toll-Free)
Fax : +91 22 4227 0338
E-mail : info.india@fluke.com
Web : www.fluke.com/india



Your nearest representative

