

TECHNICAL DATA

Fluke Networks Pro3000™ Tone Generator and Probe Kit



Key features

- Send tone signal up to 10 miles (16 km) on most cables
- Analog tone generator with bed-of-nails clips, unfiltered probe
- SmartTone™ provides 5 distinct tones for exact pair identification
- Continuity testing and line polarity confirmation
- Ergonomic sleek design, 3.5 mm headphone jack

Product overview: Fluke Networks Pro3000™ Tone Generator and Probe Kit

Pro3000™ analog tone generator and probe kit uses the SmartTone™ technology, with five different tones for exact pair identification, and provides clear and precise tracing of communication cabling. Simply short the selected pair at the near or far end to change the cadence of the tone generated.

Specifications: Fluke Networks Pro3000™ Tone Generator and Probe Kit

Pro3000 Analog Toner Specifications

User interface	Slide switch selects Continuity or Tone Mode Push button switch selects SOLID, ALT or OFF Tone mode LED Continuity/Polarity LED
Solid Frequency	1000 Hz nominal
Alternating Frequency	1000/1500 Hz nominal
Over Voltage Protection	60 Vdc in Toner/Polarity Mode
Output Power in Tone Mode	8 dbm into 600 ohms
Output Voltage Level in Continuity Mode	8 Vdc with fresh battery
Battery	9V alkaline
Temperature	Operating: -20° C to 60° C, Storage: -40° C to 70° C
Case dimensions	2.7 in. x 2.4 in. x 1.4 in. (6.9 cm x 6.1 cm x 3.6 cm)

Pro3000 Analog Probe Specifications

User interface	ON/OFF push button Volume dial Replaceable tip 3.5 mm earphone jack
Battery	9V alkaline
Temperature	Operating: -20° C to 60° C, Storage: -40° C to 70° C
Case dimensions	9.8 in. x 1.6 in. x 1.3 in. (24.9 cm x 4.1 cm x 3.3 cm)

Ordering information



26000900

Pro3000™ analog tone generator and probe kit uses the SmartTone™ technology, with five different tones for exact pair identification, and provides clear and precise tracing of communication cabling. Simply short the selected pair at the near or far end to change the cadence of the tone generated.

Includes:

- Pro3000™ Unfiltered Probe
- Pro3000™ Analog Tone Generator

Optional accessories

Description

Fluke Networks Pro3000™ Replacement Tip Replacement tip for Pro3000/3000F series probes.



Fluke. *Keeping your world up and running.*®

Fluke Corporation
PO Box 9090, Everett, WA 98206 U.S.A.

For more information call:
In the U.S.A. (800) 443-5853
In Canada (800) 36-FLUKE
From other countries +1 (425) 446-5500
www.fluke.com

©2024 Fluke Corporation.
Specifications subject to change without notice.
03/2024

**Modification of this document is not permitted
without written permission from Fluke Corporation.**